

Solution 2000/3000 - Configuration Guide for CSVIP reporting

Modified on: Tue, 3 Sep, 2019 at 10:22 AM

On Solution 2000/3000 version 2.0, we can configure CSV-IP Reporting using the Cloud-based IP module B426-M or Cloud-based 3G GSM module B450-M + B443.

Program IP items with A-Link Plus Software or Alphanumeric codepad.

1. Select **Comm** -> **Receiver Config** -> **Transmit Format**, select **CSVIP** for Receiver 1, 2, 3 or 4.
2. Select **Comm** -> **Receiver Config** -> **Subscriber ID Number**, enter Subscriber ID Number.
3. Select **Comm** -> **Receiver Config** -> **IP + Port / Email**, enter IP and the Port, for example, 192.168.226.17:12000.
4. Select **Comm** -> **Receiver Config** -> **CSVIP User Name And Password**, enter CSVIP User Name and Password:
 - Both user name and password, enter as user name with comma and password with comma, for example, USER 1, 2580,.
 - Only user name, enter as user name with two commas, for example, USER 1,,.
 - Only password, enter as comma, followed by password with comma, for example, ,2580,.
 - No user name and password, only enter two commas.

The screenshot shows the 'Receiver Config' table in the A-Link Plus - ADMIN software. The table is configured for 'Receiver 1' through 'Receiver 4'. The 'Transmit Format' is set to 'CSVIP', the 'Subscriber ID Number' is '004444', and the 'IP + Port / Email' is '192.168.226.17:12000'. The 'CSVIP User Name...' field is currently empty. The table also shows other parameters like 'Conetix ACK Wait...', 'Conetix Heart Be...', and 'Conetix Anti-Repl...'.

Parameter Name	Receiver 1	Receiver 2	Receiver 3	Receiver 4
First Phone Number				
Second Phone Nu...				
Transmit Format	CSVIP	Contact ID	Contact ID	Contact ID
Subscriber ID Nu...	004444	000000	000000	000000
IP + Port / Email	192.168.226.17:12000			
CSVIP User Name...				
Conetix ACK Wait...	5	5	5	5
Conetix Heart Be...	1	1	1	1
Conetix Anti-Repl...	Enable	Enable	Enable	Enable

5. Select **Comm** -> **Network Config**, select module 1 or 2 as **Use, B4xx-M**.

Panel Series: One Solution | Panel Type: Solution 3000_V2.00 | Last Panel Modification: 2019-09-02 12:04:20

- Output
 - Onboard Output
 - Codepad Output
 - Extend Output
 - Siren Config
 - Output Name
- Comm
 - Receiver Config
 - Network Config**
 - Report Config

Parameter Name	Parameter Value
Network Module 1	Use, B4xx-M
Network Module 2	Not used
A-Link/RSC Password	0000000000